

# Hytera DMR APRS GPS

---

## Positioning on Hytera CPS:

- Conventional -> General -> Accessories:
- GPS = On, GPS Data Compression = Off
- Just configure preferred location report mode at GPS Trigger section
- Conventional -> General -> Network
- RRS & GPS Radio ID: 262999
- preferred channel settings:
- IP Multi-site Connect: On
- GPS Revert Channel: Selected
- RRS Revert Channel: Selected

# Motorola DMR APRS GPS

---

## Positioning on Motorola CPS:

- General:
- GPS: On
- Network:
- CAI Network: 12
- ARS Radio ID: 262999
- preferred channel settings:
- ARS: On System/Site Change
- IP Site Connect: On
- GPS Revert: Selected
- Data Call Confirmed: On

It is also possible to configure Telemetry (server at the same ID 262999)

**Now about messaging.**

**Any SMS that send to callsign and SSID configured at Users table will be delivered to you radio.**

**To send SMS to APRS: just send SMS to privat**

**Echo function (Parrot): TG262997 (private Call)**